

FEATURE

- Unique creation of custom password, Can prevent other user read the parameter from machine and PC interface.
- Comes with engineering lock function, password could be set ,customize the boot times.
- Could preset 3 mode, easy operate.
- A karaoke effector with a speaker processor, each function could be adjust independently.
- Adopt 24Bit data bus and 32 Bit DSP
- MUSIC has set 7 segment of PEQ. High-pass filter for music main output: 12dB-24dB (0Hz-303Hz)
- MIC has set 2 group of 15 segments PEQ, A/B channel adjusted independently.
- Main output has 5 segments PEQ,and also has compress / limit function.
- Centre-Channel output,rear-channel output and subwoofer all have 5 segments PEQ .
- The microphone has 4 type feedback suppressed, and you could select OFF, 1,2,3.
- 15 modes could be saved .
- Microphone output, main output, centre-channel output, subwoofer output, rear-channel output all have compress/limit and delay function.
- There are administer mode and user mode. The user mode could not save data after adjusted parameter.
- This machine had full-function menu, and you could set the parameter through PC interface.

TECHNICAL DATA

MAX input electrical level for music	4V (RMS)
MAX output electrical level for output CH	4V (RMS)
Music gain	MAX : 12dB
Microphone sensitivity	64mV (Out : 4V)
S/N	>80dB
Power supplied	220V/AC/50Hz
Size	483 x 218.5 x 47.5mm

