

## FEATURE

- Unique creation of custom password, Can prevent other user read the parameter from machine and PC interface.
- Comes with engineering lock function, password could be set ,customize the boot times.
- Could preset 3 mode, easy operate.
- A karaoke effector with a speaker processor, each function could be adjust independently.
- Adopt 24Bit data bus and 32 Bit DSP
- MUSIC has set 7 segment of PEQ. High-pass filter for music main output: 12dB-24dB (0Hz-303Hz)
- MIC has set 2 group of 15 segments PEQ, A/B channel adjusted independently.
- Main output has 5 segments PEQ,and also has compress / limit function.
- Centre-Channel output,rear-channel output and subwoofer all have 5 segments PEQ .
- The microphone has 4 type feedback suppressed, and you could select OFF,1,2,3.
- 15 modes could be saved .
- Microphone output, main output, centre-channel output, subwoofer output, rear-channel output all have compress/limit and delay function.
- There are administer mode and user mode. The user mode could not save data after adjusted parameter.
- This machine had full-function menu, and you could set the parameter through PC interface.

## TECHNICAL DATA

<b>MAX input electrical level for music</b>	4V (RMS)
<b>MAX output electrical level for output CH</b>	4V (RMS)
<b>Music gain</b>	<b>MAX</b> : 12dB
<b>Microphone sensitivity</b>	64mV (Out : 4V)
<b>S/N</b>	>80dB
<b>Power supplied</b>	220V/AC/50Hz
<b>Size</b>	483 x 218.5 x 47.5mm

