

# U600-HA2

## TECHNICAL DATA

### U600-HA2 RECEIVER:

<b>Frequency band</b>	UHF640-690MHz
<b>Total number of channels</b>	200 groups
<b>Working mode</b>	PLL phase-locked loop circuit
<b>Dynamic range</b>	> 110dB
<b>Distortion</b>	0.5%
<b>Frequency response</b>	30Hz-20KHz
<b>Signal-to-noise ratio</b>	>90dB
<b>Effective use distance</b>	150M
<b>Power supply</b>	12V 1000mA
<b>Audio output interface</b>	1*6.3mm,2*XLR balanced output
<b>Receiver Principle</b>	True Diversity
<b>Product size</b>	480*221*45mm

### U600-HA2 HANDHELD TRANSMITTER PARAMETERS:

<b>Transmitter power</b>	10mw or 5mw
<b>Working mode</b>	PLL phase-locked loop circuit
<b>Use battery type</b>	2AA
<b>Mirror image response</b>	>50dB
<b>Frequency range</b>	30Hz-20KHz
<b>Product size</b>	50*255mm

